

The following settings need to be changed to enable the full Windows character set.

Full 256 ASCII Character Set for AstroJet Printer

The AstroJet 1000/III software uses the basic 128-character set to print the addresses. This speeds up downloading of the fonts and is more efficient. In some cases it may be necessary to use the entire 256 ASCII character set to print the addresses. European addresses that use accent marks over certain letters for example. In order to activate the entire 256 ASCII character set it is necessary to modify the registry file in windows. If you are not familiar with modifying registries in Windows, get help.

1. Click on START, then RUN. Enter "REGEDIT" in **Open:** then click **OK**.
2. Enter the following tree:
 HKEY_CURRENT_USER
 Software
 Astro Machine Corp
 AstroJet 1000-5 (Depending on model no.)
 Options
 Windows Char Set

3. Double Click on Windows Char Set icon.
4. Change "0" to "1". Then Click **OK**
5. Click on **Registry**, then **Exit** to exit the program and save the changes.
6. Open AstroJet Printer Control Panel and click on **Properties...**
7. Click on **Cache**, then click on **Flush Fonts** then click **OK**.

NOTE: You must flush the fonts and re-render them to get the special characters to print.

8. Reload the print job and print.

NOTE: Once this change is made it is permanent in the registry. To change it reenter the Registry and change the "1" to "0" then flush the fonts.

